



## DFX VersaBar IP65 and Indoor DMX Profiles

### 4 Channel Mode

- 1 Red
- 2 Green
- 3 Blue
- 4 White

### 6 Channel Mode

- 1 Intensity
- 2 Red
- 3 Green
- 4 Blue
- 5 White
- 6 Strobe

### 8 Channel Mode

- 1 Intensity
- 2 Red
- 3 Green
- 4 Blue
- 5 White
- 6 Chase
- 7 Chase Speed
- 8 Strobe

### 56 Channel Mode

- 1 Red
- 2 Green
- 3 Blue
- 4 White
- 5-56 Repeats 1-4

Following existing fixtures possibly in your fixture library may work with our fixture:

- Eliminator Lighting > Mini Par RGBW LED (4, 6, 8 Channel Modes Only)
- Snow Lighting > SnowARC Pro Quad 40 (4, 6, 8 Channel Modes Only)